Sensear's Programming Tablet (PRGTAB01)

Description
Laser 7-inch Android 16GB tablet comes pre-loaded with the latest operating system and Sensear's programming software for headset programming made easy.

Specifications

Battery	2000mAh
Camera	Front and Rear
CPU	Quad Core Processor
Memory	16GB Internal Storage
Micro SD Card Slot	Yes
Operating System	Android 10 Go Edition
Packaging Dimensions	13.4cm x 3.7cm x 21.1cm
RAM	2GB
Resolution	1024 x 600
Screen Size	7"
Bluetooth	Yes
Weight	0.25kg

Operating System and Connectivity
The Laser 7 Inch Android 16GB Tablet runs on Android 10 Go Edition with the latest lightning speed OS. This new OS makes the app starting time 15% faster than the previous OS versions. It also features Bluetooth and Wi-Fi Connectivity.

Processor
Powered by a quad-core processor, this latest tablet has multi-core capabilities for allowing you to handle more tasks in less time. You can easily run multiple apps on this device simultaneously with smooth performance.

Display
The high resolution (1024 x 600) 7-inch LCD screen of the tablet display adds life to the images, no matter your viewing angle.

Camera
The tablet comes integrated with front and rear camera that brings life to images with superior picture quality.

Battery
The tablet has a 2000mAh battery that's intended to last for up to 6 hours. You may even extend the battery life by reducing the brightness, turning off Bluetooth, turning off Wi-Fi and turning off other features that you don't require in the moment.

Sensear Pty Ltd, 199 Great Eastern Highway, Belmont, Western Australia 6104, Australia
Toll Free: 1-300-859-120   Tel: +61 8 9277 7338   (USA Office Toll Free: 1-888-973-6732)